

# 8.8 Users

## Edit groups

GROUPS OVERVIEW		
Groups	Status	Actions
administrator	Authorization level: 11	Edit Delete
engineer	Authorization level: 5	Edit Delete
operator	Authorization level: 3	Edit Delete
viewer	Authorization level: 1	Edit Delete
Add New Group...		

On this page user groups can be edited, deleted or added.

Groups: name of the user group

Status: shows authorization level set to specific user group. The higher the lever, the higher authorization requirements.

Actions: edit or delete user group

## Add new group

Group Name	<input type="text"/>
Access level	-- Please choose --
<small>Access level this group refers to. Use with external PAM module (e.g. RADIUS)</small>	
Enable Phub menus	<input type="checkbox"/> View <input type="checkbox"/> Edit
Enable Users menus	<input type="checkbox"/> View <input type="checkbox"/> Edit
Enable Services menus	<input type="checkbox"/> View <input type="checkbox"/> Edit
Enable Status menus	<input type="checkbox"/> View <input type="checkbox"/> Edit
Enable Network menus	<input type="checkbox"/> View <input type="checkbox"/> Edit
Enable System menus	<input type="checkbox"/> View <input type="checkbox"/> Edit
Back to Overview Save & Apply Save Reset	

Configuration window for new group. After group name is determined, acc ess level and permissions can be set.

## Edit users

USERS OVERVIEW		
Users	Status	Actions
user	SSH Access: Enabled Group: viewer Date Added: Wed Jul 12 08:53:00 2023 Last Entry: undefined	Edit Change Password Delete
Add New User...		

On edit users window list of all the users is shown.

Users: user name

Status: shows if SSH access is enabled and which group the user belongs to.

Actions: edit, delete or change password for the user

Add new user

User Name

User Group

viewer


▼

SSH Access

Enabled

▼

Password



Back to Overview

Save & Apply

Save

Reset

Configuration window for new user. To create a new user, name and password should be created and user group and SSH access should be set.

Password

Password



Confirmation



Save & Apply

Save

Reset

Changes password of the device.