

8.8 Users

Edit groups

GROUPS OVERVIEW		
Groups	Status	Actions
administrator	Authorization level: 11	Edit Delete
engineer	Authorization level: 5	Edit Delete
operator	Authorization level: 3	Edit Delete
viewer	Authorization level: 1	Edit Delete
Add New Group...		

On this page user groups can be edited, deleted or added.

Groups: name of the user group

Status: shows authorization level set to specific user group. The higher the lever, the higher authorization requirements.

Actions: edit or delete user group

Add new group

Group Name	<input type="text"/>
Access level	-- Please choose --
<small>Access level this group refers to. Use with external PAM module (e.g. RADIUS)</small>	
Enable Phub menus	<input type="checkbox"/> View <input type="checkbox"/> Edit
Enable Users menus	<input type="checkbox"/> View <input type="checkbox"/> Edit
Enable Services menus	<input type="checkbox"/> View <input type="checkbox"/> Edit
Enable Status menus	<input type="checkbox"/> View <input type="checkbox"/> Edit
Enable Network menus	<input type="checkbox"/> View <input type="checkbox"/> Edit
Enable System menus	<input type="checkbox"/> View <input type="checkbox"/> Edit
Back to Overview Save & Apply Save Reset	

Configuration window for new group. After group name is determined, acc ess level and permissions can be set.

Edit users

USERS OVERVIEW		
Users	Status	Actions
user	SSH Access: Enabled Group: viewer Date Added: Wed Jul 12 08:53:00 2023 Last Entry: undefined	Edit Change Password Delete
Add New User...		

On edit users window list of all the users is shown.

Users: user name

Status: shows if SSH access is enabled and which group the user belongs to.

Actions: edit, delete or change password for the user

Add new user

User Name

User Group

viewer


▼

SSH Access

Enabled

▼

Password



Back to Overview

Save & Apply

Save

Reset

Configuration window for new user. To create a new user, name and password should be created and user group and SSH access should be set.

Password

Password



Confirmation



Save & Apply

Save

Reset

Changes password of the device.